

AUTOMATIC TRANSFER SWITCH BOX INCLUDED

SINGLE PHASE  
230 V / 50 Hz  
GASOLINE

3 YEARS  
WARRANTY

MAX OUTPUT  
7 kW

LONG RUN  
TANK

ELECTRIC  
START



powered by



**AUTOMATIC TRANSFER SWITCH BOX:** Thanks to this device, you can turn your portable generator into an alternative power source in case of a power outage. It is an electrical cabinet that serves as an interface between the mains supply and your generator. When the mains power goes out, the electrical cabinet starts your generator. When the power returns, the cabinet shuts off the generator. Only for generators equipped with a DES module and/or ILME socket.

Equipped with a premium engine, known for its reliability and designed for intensive use, the EXPLORER range is dedicated to all professional user. Designed for frequent, heavy-use and longer run times.

## EXPLORER 7510 XL27 AVR DE N/S

Type		1 phase
Voltage regulator		Capacitor
Maximum AC output	kW	7
Continuous operating power (COP)	kW	5
Maximum Amps	A	30.4
AC voltage	V	230
Frequency	Hz	50
Noise level EEC (LwA)	dB(A)	97
Noise level @ 7 m	dB(A)	72
Engine		WORMS EX40
Maximum output	HP	14
Fuel type		PETROL RON 95
Fuel tank capacity	L	25
Autonomy (@ ¾ of the continuous output)	h	7 h 30
Dimensions L x W x H	mm	870 x 570 x 610
Packaging dimensions L x W x H	mm	890 x 590 x 630
Net weight	kg	83.5
Gross weight	kg	85.5
Reference		2V000026

## STANDARD EQUIPMENT

- ✓ OHC, 4-stroke gasoline engine
- ✓ DE: Electric start + Battery
- ✓ Recoil starter
- ✓ Electronic oil sensor security
- ✓ ATS: Mains Failure Automatic Transfer Switch
- ✓ AVR: Automatic Voltage Regulation
- ✓ 1 Single phase socket 10/16 A Schuko 230 V
- ✓ 1 EC Single phase socket 230 V / 32 A
- ✓ Sockets protected by thermal circuit breaker

## EQUIPMENT OPTIONAL

- ✓ Wheelbarrow kit N/360
- ✓ Circuit breaker kit (factory option): 30 mA circuit breaker + Copper Ground Rod + box



Optional accessory  
Male plug n°2 - 32 A - 230 V