

SINGLE PHASE
230 V / 50 Hz
GASOLINE

**3 YEARS
WARRANTY**

MAX OUTPUT
9.2 KW

LONG RUN
TANK

ELECTRIC
START



Optional accessory
Male plug n°2 - 32 A - 230 V



powered by
YANMAR

Combine with OHV engine technology, Leader rang bring you the choice of a longer run times generator, with serial electric start.

LEADER 10500 XL21 DE

Type		1 phase
Voltage regulator		Capacitor
Maximum AC output	kW	9.2
Continuous operating power (COP)	kW	7.2
Maximum Amps	A	40
AC voltage	V	230
Frequency	Hz	50
Noise level EEC (LwA)	dB(A)	104
Noise level @ 7 m	dB(A)	79
Engine		YAMAHA EH65
Maximum output	HP	22
Fuel type		PETROL RON 95
Fuel tank capacity	L	21
Autonomy (@ ¾ of the continuous output)	h	6 h 10
Dimensions L x W x H	mm	935 x 575 x 575
Packaging dimensions L x W x H	mm	960 x 610 x 600
Net weight	kg	99
Gross weight	kg	101
Reference		2V0000030

STANDARD EQUIPMENT

- ✓ OHV, 4-stroke gasoline engine
- ✓ DE: Electric start + Battery
- ✓ Low oil pressure security
- ✓ Low oil alert
- ✓ Large tank
- ✓ Fuel gauge
- ✓ 1 Single phase socket 10/16 A Schuko 230 V
- ✓ 1 EC Single phase socket 230 V / 32 A
- ✓ Sockets protected by thermal circuit breaker

EQUIPMENT OPTIONAL

- ✓ Wheelbarrow kit N/360 535
- ✓ AVR: Automatic Voltage Regulation (factory option)
- ✓ Kit interdif (factory option): 30 mA interdifferentiel kit + Copper Ground Rod + box